

---

# **pylibftdi Documentation**

*Release 0.15.0*

**Ben Bass**

**Oct 27, 2019**



<b>1</b>	<b>Contents</b>	<b>3</b>
1.1	Introduction . . . . .	3
1.2	Quick Start . . . . .	5
1.3	Installation . . . . .	6
1.4	Basic Usage . . . . .	8
1.5	Bit-bang mode . . . . .	9
1.6	Serial mode . . . . .	10
1.7	Advanced Usage . . . . .	12
1.8	pylibftdi questions . . . . .	12
1.9	pylibftdi troubleshooting . . . . .	18
1.10	pylibftdi Package . . . . .	20
<b>2</b>	<b>Indices and tables</b>	<b>33</b>
	<b>Python Module Index</b>	<b>35</b>
	<b>Index</b>	<b>37</b>



pylibftdi is a simple library interacting with FTDI devices to provide serial and parallel IO from Python.

Example Usage:

```
>>> from pylibftdi import BitBangDevice
>>> with BitBangDevice('FT0123') as dev:
...     dev.port.bit[0] = 1
```

The two main use cases it serves are:

- the need to control or monitor external equipment, for which a FTDI module may be a cheap and reliable starting point.
- the need to interact with existing devices which are known to contain FTDI chipsets for their USB interface.

FTDI (<http://www.ftdichip.com>) create devices (chipsets, modules, cables etc) to interface devices to the USB port of your computer.

libftdi (<http://www.intra2net.com/en/developer/libftdi/>) is an open source driver to communicate with these devices, and runs on top of libusb. It works on Windows, Linux, and Mac OS X, and likely other systems too.

pylibftdi is a pure Python module which interfaces (via ctypes) to libftdi, exposing a simple file-like API to connected devices. It supports serial and parallel IO in a straight-forward way, and aims to be one of the simplest ways of interacting with the world outside your PC.



## 1.1 Introduction

`pylibftdi` is a minimal Pythonic interface to FTDI devices using `libftdi`<sup>1</sup>.

### Features

- Supports Python 2 and Python 3
- Supports parallel and serial devices
- Support for multiple devices
- File-like interface wherever appropriate
- Cross-platform

### Limitations

- The API might change prior to reaching a 1.0 release.

### 1.1.1 Usage

The primary interface is the `Device` class in the `pylibftdi` package; this gives serial access on relevant FTDI devices (e.g. the UM232R), providing a file-like interface (read, write). Baudrate is controlled with the `baudrate` property.

If a `Device` instance is created with `mode='t'` (text mode) then `read()` and `write()` can use the given `encoding` (defaulting to `latin-1`). This doesn't make a lot of difference on Python 2 (and can be omitted), but allows easier integration with passing unicode strings between devices in Python 3.

Multiple devices are supported by passing the desired device serial number (as a string) in the `device_id` parameter - this is the first parameter in both `Device()` and `BitBangDevice()` constructors. Alternatively the device 'description' can be given, and an attempt will be made to match this if matching by serial number fails.

---

<sup>1</sup> <http://www.intra2net.com/en/developer/libftdi/>

## Examples

```
>>> from pylibftdi import Device
>>>
>>> with Device(mode='t') as dev:
...     dev.baudrate = 115200
...     dev.write('Hello World')
```

The `pylibftdi.BitBangDevice` wrapper provides access to the parallel IO mode of operation through the `port` and `direction` properties. These provide an 8 bit IO port including all the relevant bit operations to make things simple.

```
>>> from pylibftdi import BitBangDevice
>>>
>>> with BitBangDevice('FTE00P4L') as bb:
...     bb.direction = 0x0F # four LSB are output (1), four MSB are
...     ↪input (0)
...     bb.port |= 2 # set bit 1
...     bb.port &= 0xFE # clear bit 0
```

There is support for a number of external devices and protocols, including interfacing with HD44780 LCDs using the 4-bit interface.

### 1.1.2 History & Motivation

This package is the result of various bits of work using FTDI's devices, primarily for controlling external devices. Some of this is documented on the `codedstructure` blog, `codedstructure.blogspot.com`

Several other open-source Python FTDI wrappers exist, and each may be best for some projects. Some aim at closely wrapping the `libftdi` interface, others use FTDI's own D2XX driver (`ftd2xx`<sup>2</sup>) or talk directly to USB via `libusb` or similar (such as `pyftdi`<sup>3</sup>).

The aim for `pylibftdi` is to work with `libftdi`, but to provide a high-level Pythonic interface. Various wrappers and utility functions are also part of the distribution; following Python's batteries included approach, there are various interesting devices supported out-of-the-box - or at least there will be soon!

### 1.1.3 Plans

- Add more examples: SPI devices, knight-rider effects, input devices, MIDI...
- Perhaps add support for D2XX driver, though the name then becomes a slight liability ;)

### 1.1.4 License

Copyright (c) 2010-2015 Ben Bass <[benbass@codedstructure.net](mailto:benbass@codedstructure.net)>

`pylibftdi` is released under the MIT licence; see the file "LICENSE.txt" for information.

All trademarks referenced herein are property of their respective holders. `libFTDI` itself is developed by Intra2net AG. No association with Intra2net is claimed or implied, but I have found their library helpful and had fun with it...

---

<sup>2</sup> <http://pypi.python.org/pypi/ftd2xx>

<sup>3</sup> <https://github.com/eblot/pyftdi>



## 1.2 Quick Start

### 1.2.1 Install pylibftdi

See the [installation](#) instructions for more detailed requirements, but hopefully things will work by just running the following:

```
$ pip install pylibftdi
```

### 1.2.2 Connect and enumerate FTDI devices

Connect the FTDI device to a free USB port. Run the `list_devices` example to enumerate connected FTDI devices:

```
$ python -m pylibftdi.examples.list_devices
```

For each connected device, this will show manufacturer, model identifier, and serial number. With a single device connected, the output maybe something like the following:

```
FTDI:UM232H:FTUBIOWF
```

Though hopefully with a different serial number, or else you've either stolen mine, or you are me...

### 1.2.3 Test some actual IO

#### Output example

Connect an LED between D0 of your bit-bang capable device and ground, via a 330 - 1K ohm resistor as appropriate.

Test the installation and functioning of pylibftdi with the following:

```
$ python -m pylibftdi.examples.led_flash
```

The LED should now flash at approximately 1Hz.

#### Input example

To test some input, remove any connections from the port lines initially, then run the following, which reads and prints the status of the input lines regularly:

```
$ python -m pylibftdi.examples.pin_read
```

The `pin_read` example is a complete command line application which can be used to monitor for particular values on the attached device pins, and output an appropriate error code on match. Repeat the above with a trailing `--help` for info.

## 1.3 Installation

Unsurprisingly, *pylibftdi* depends on *libftdi*, and installing this varies according to your operating system. Chances are that following one of the following instructions will install the required prerequisites. If not, be aware that *libftdi* in turn relies on *libusb*.

Installing *pylibftdi* itself is straightforward - it is a pure Python package (using *ctypes* for bindings), and has no dependencies outside the Python standard library for installation. Don't expect it to work happily without *libftdi* installed though :-)

```
$ pip install pylibftdi
```

Depending on your environment, you may want to use either the `--user` flag, or prefix the command with `sudo` to gain root privileges.

### 1.3.1 Windows

I perform only limited testing of *pylibftdi* on Windows, but it should work correctly provided the requirements of *libftdi* and *libusb* are correctly installed.

Recent *libftdi* binaries for Windows seem to be available from the [picusb<sup>4</sup>](#) project on Sourceforge. Download `libftdi1-1.1_devkit_x86_x64_21Feb2014.zip` or later from that site, which includes the required

Installing libraries on Windows is easier with recent versions of Python (2.7.9, 3.4+) installing *pip* directly, so the standard approach of *pip install pylibftdi* will now easily work on Windows.

### 1.3.2 Mac OS X

I suggest using [homebrew<sup>5</sup>](#) to install *libftdi*:

```
$ brew install libftdi
```

On OS X Mavericks (and presumably future versions) Apple include a driver for FTDI devices. This needs unloading before *libftdi* can access FTDI devices directly. See the [Troubleshooting](#) section for instructions.

### 1.3.3 Linux

There are two steps in getting a sensible installation in Linux systems:

1. Getting `libftdi` and its dependencies installed
2. Ensuring permissions allow access to the device without requiring root privileges. Symptoms of this not being done are programs only working properly when run with `sudo`, giving '-4' or '-8' error codes in other cases.

Each of these steps will be slightly different depending on the distribution in use. I've tested *pylibftdi* on Debian Wheezy (on a Raspberry Pi), Ubuntu (various versions, running on a fairly standard ThinkPad laptop), and Arch Linux (running on a PogoPlug - one of the early pink ones).

---

<sup>4</sup> <http://sourceforge.net/projects/picusb/files/>

<sup>5</sup> <http://mxcl.github.com/homebrew/>

## Debian (Raspberry Pi) / Ubuntu etc

On Debian like systems (including Ubuntu, Mint, Debian, etc), the package *libftdi-dev* should give you what you need as far as the libftdi library is concerned:

```
$ sudo apt-get install libftdi-dev
```

The following works for both a Raspberry Pi (Debian Wheezy) and Ubuntu 12.04, getting ordinary users (e.g. 'pi' on the RPi) access to the FTDI device without needing root permissions:

1. Create a file `/etc/udev/rules.d/99-libftdi.rules`. You will need sudo access to create this file.
2. Put the following in the file:

```
SUBSYSTEMS=="usb", ATTRS{idVendor}=="0403", ATTRS{idProduct}=="6001", ↵
↳GROUP="dialout", MODE="0660"
SUBSYSTEMS=="usb", ATTRS{idVendor}=="0403", ATTRS{idProduct}=="6014", ↵
↳GROUP="dialout", MODE="0660"
```

Some FTDI devices may use other USB PIDs. You could try removing the match on *idProduct* altogether, just matching on the FTDI vendor ID. Or Use *lsusb* or similar to determine the exact values to use (or try checking *dmesg* output on device insertion / removal). `udevadm monitor --environment` is also helpful, but note that the environment 'keys' it gives are different to the attributes (filenames within `/sys/devices/...`) which the ATTRS will match. Perhaps `ENV{}` matches work just as well, though I've only tried matching on ATTRS.

Note that changed udev rules files will be picked up automatically by the udev daemon, but will only be acted upon on device actions, so unplug/plug in the device to check whether you're latest rules iteration actually works :-)

See <http://wiki.debian.org/udev> for more on writing udev rules.

## Arch Linux

The *libftdi* package (sensibly enough) provides the *libftdi* library:

```
$ sudo pacman -S libftdi
```

Similar udev rules to those above for Debian should be included (again in `/etc/udev/rules.d/99-libftdi.rules` or similar), though the GROUP directive should be changed to set the group to 'users':

```
SUBSYSTEMS=="usb", ATTRS{idVendor}=="0403", ATTRS{idProduct}=="6001", ↵
↳GROUP="users", MODE="0660"
SUBSYSTEMS=="usb", ATTRS{idVendor}=="0403", ATTRS{idProduct}=="6014", ↵
↳GROUP="users", MODE="0660"
```

### 1.3.4 Testing installation

Connect your device, and run the following (as a regular user):

```
$ python -m pylibftdi.examples.list_devices
```

If all goes well, the program should report information about each connected device. If no information is printed, but it is when run with `sudo`, a possibility is permissions problems - see the section under Linux above regarding udev rules.

If the above works correctly, then try the following:

```
$ python -m pylibftdi.examples.led_flash
```

Even without any LED connected, this should ‘work’ without any error - quit with Ctrl-C. Likely errors at this point are either permissions problems (e.g. udev rules not working), or not finding the device at all - although the earlier stage is likely to have failed if this were the case.

Feel free to contact me (@codedstructure) if you have any issues with installation, though be aware I don’t have much in the way of Windows systems to test.

## 1.4 Basic Usage

*pylibftdi* is a minimal Pythonic interface to FTDI devices using [libftdi](#)<sup>6</sup>. Rather than simply expose all the methods of the underlying library directly, it aims to provide a simpler API for the main use-cases of serial and parallel IO, while still allowing the use of the more advanced functions of the library.

### 1.4.1 General

The primary interface is the `Device` class in the `pylibftdi` package; this gives serial access on relevant FTDI devices (e.g. the UM232R), providing a file-like interface (read, write). Baudrate is controlled with the `baudrate` property.

If a `Device` instance is created with `mode='t'` (text mode) then `read()` and `write()` can use the given `encoding` (defaulting to latin-1). This doesn’t make a lot of difference on Python 2 (and can be omitted), but allows easier integration with passing unicode strings between devices in Python 3.

Multiple devices are supported by passing the desired device serial number (as a string) in the `device_id` parameter - this is the first parameter in both `Device()` and `BitBangDevice()` constructors. Alternatively the device ‘description’ can be given, and an attempt will be made to match this if matching by serial number fails.

In the event that multiple devices (perhaps of identical type) have the same description and serial number, the `device_index` parameter may be given to open matching devices by numerical index; this defaults to zero, meaning the first matching device.

### Examples

```
>>> from pylibftdi import Device
>>>
>>> with Device(mode='t') as dev:
...     dev.baudrate = 115200
...     dev.write('Hello World')
```

---

<sup>6</sup> <http://www.intra2net.com/en/developer/libftdi/>

The `pylibftdi.BitBangDevice` wrapper provides access to the parallel IO mode of operation through the `port` and `direction` properties. These provide an 8 bit IO port including all the relevant bit operations to make things simple.

```
>>> from pylibftdi import BitBangDevice
>>>
>>> with BitBangDevice('FTE00P4L') as bb:
...     bb.direction = 0x0F # four LSB are output (1), four MSB are
↳input (0)
...     bb.port |= 2        # set bit 1
...     bb.port &= 0xFE    # clear bit 0
```

There is support for a number of external devices and protocols, specifically for interfacing with HD44780 LCDs using the 4-bit interface.

## 1.5 Bit-bang mode

Bit-bang mode allows the programmer direct access (both read and write) to the state of the IO lines from a compatible FTDI device.

The interface provided by FTDI is intended to mirror the type of usage on a microcontroller, and is similar to the ‘user port’ on many old 8-bit computers such as the BBC Micro and Commodore 64.

The basic model is to have two 8 bit ports - one for data, and one for ‘direction’. The data port maps each of the 8 bits to 8 independent IO signals, each of which can be configured separately as an ‘input’ or an ‘output’.

In `pylibftdi`, the data port is given by the `port` attribute of a `BitBangDevice` instance, and the direction control is provided by the `direction` attribute. Both these attributes are implemented as Python properties, so no method calls are needed on them - simple read and write in Python-land converts to read and write in the physical world seen by the FTDI device.

The direction register maps to

where each bit maps to a separate digital signal,

### 1.5.1 Read-Modify-Write

Port vs Latch

Via the augmented assignment operations, `pylibftdi BitBangDevice` instances support read-modify-write operations, such as arithmetic (`+=` etc), bitwise (`&=`), and other logical operations such as shift (`<<=`)

### Examples

```
>>> from pylibftdi import BitBangDevice
>>>
>>> with BitBangDevice('FTE00P4L') as bb:
...     bb.direction = 0x0F # four LSB are output (1), four MSB are
↳input (0)
...     bb.port |= 2        # set bit 1
```

(continues on next page)

(continued from previous page)

```
...     bb.port &= 0xFE         # clear bit 0

>>> with BitBangDevice() as bb:
...     bb.port = 1
...     while True:
...         # Rotate the value in bb.port
...         bb.port = ((bb.port << 1) | ((bb.port >> 8) & 1)) & 0xFF
...         time.sleep(1)
```

## 1.5.2 The *Bus* class

Dealing with bit masks and shifts gets messy quickly. Some languages such as C and C++ provide direct support for accessing bits - or series of consecutive bits - with bitfields. The `Bus` class provides the facility to provide a similar level of support to pylibftdi `BitBangDevice` classes.

As an example, consider an HD44780 LCD display. These have a data channel of either 4 or 8 bits, and a number of additional status lines - `rs` which acts as a register select pin - indicating whether a data byte is a command (0) or data (1), and `e` - clock enable.:

```
class LCD(object):
    """
    The UM232R/245R is wired to the LCD as follows:
    DB0..3 to LCD D4..D7 (pin 11..pin 14)
    DB6 to LCD 'RS' (pin 4)
    DB7 to LCD 'E' (pin 6)
    """
    data = Bus(0, 4)
    rs = Bus(6)
    e = Bus(7)
```

## 1.6 Serial mode

The default mode of pylibftdi devices is to behave as a serial UART device, similar to the 'COM1' device found on older PCs. Nowadays most PCs operate with serial devices over USB-serial adapters, which may often include their own FTDI chips. To remain compatible with the RS232 standard however, these adapters will often include level-shifting circuitry which is of no benefit in communicating with other circuits operating at the 3.3 or 5 volt levels the FTDI hardware uses.

The default serial configuration is 9600 baud, 8 data bits, 1 stop bit and no parity (sometimes referred to as 8-N-1<sup>7</sup>). This is the default configuration of the old 'COM' devices back to the days of the original IBM PC and MS-DOS.

### 1.6.1 Setting line parameters

Changing line parameters other than the baudrate is supported via use of the underlying FTDI function calls.

---

<sup>7</sup> <http://en.wikipedia.org/wiki/8-N-1>

## 1.6.2 The SerialDevice class

While the standard `Device` class supports standard `read` and `write` methods, as well as a `baudrate` property, further functionality is provided by the `SerialDevice` class, available either as a top-level import from `pylibftdi` or through the `serial_device` module. This subclasses `Device` and adds additional properties to access various control and handshake lines.

The following properties are available:

property	meaning	direction
<code>cts</code>	Clear To Send	Input
<code>rts</code>	Ready To Send	Output
<code>dsr</code>	Data Set Ready	Input
<code>dtr</code>	Data Transmit Ready	Output
<code>ri</code>	Ring Indicator	Input

Note that these lines are normally active-low, and `pylibftdi` makes no attempt to hide this from the user. It is impractical to try to ‘undo’ this inversion in any case, since it can be disabled in the EEPROM settings of the device. Just be aware if using these lines as GPIO that the electrical sense will be the opposite of the value read. The lines are intended to support handshaking rather than GPIO, so this is not normally an issue; if CTS is connected to RTS, then values written to RTS will be reflected in the value read from CTS.

## 1.6.3 Subclassing `Device` - A MIDI device

To abstract application code from the details of any particular interface, it may be helpful to subclass the `Device` class, providing the required configuration in the `__init__` method to act in a certain way. For example, the MIDI<sup>8</sup> protocol used by electronic music devices is an asynchronous serial protocol operating at 31250 baud, and with the same 8-N-1 parameters which `pylibftdi` defaults to.

Creating a `MidiDevice` subclass of `Device` is straightforward:

```
class MidiDevice(Device):
    "subclass of pylibftdi.Device configured for MIDI"

    def __init__(self, *o, **k):
        Device.__init__(self, *o, **k)
        self.baudrate = 31250
```

Note it is important that the superclass `__init__` is called first; calling it on an uninitialised `Device` would fail, and even if it succeeded, the superclass `__init__` method resets `baudrate` to 9600 anyway to ensure a consistent setup for devices which may have been previously used with different parameters.

Use of the `MidiDevice` class is simple - as a `pylibftdi` `Device` instance, it provides a file-based API. Simply `read()` and `write()` the data to an instance of the class:

```
>>> m = MidiDevice()
>>> m.write('\x90\x80\x80')
>>> time.sleep(1)
>>> m.write('\x80\x00')
```

<sup>8</sup> <http://www.midi.org>

## 1.7 Advanced Usage

### 1.7.1 libftdi function access

Three attributes of `Device` instances are documented which allow direct access to the underlying `libftdi` functionality.

1. `fdll` - this is a reference to the loaded `libftdi` library, loaded via `ctypes`. This should be used with the normal `ctypes` protocols.
2. `ctx` - this is a reference to the context of the current device context. It is managed as a raw `ctypes` byte-string, so can be modified if required at the byte-level using appropriate `ctypes` methods.
3. `ftdi_fn` - a convenience function wrapper, this is the preferred method for accessing library functions for a specific device instance. This is a function forwarder to the local `fdll` attribute, but also wraps the device context and passes it as the first argument. In this way, using `device.ftdi_fn.ft_xyz` is more like the D2XX driver provided by FTDI, in which the device context is passed in at initialisation time and then the client no longer needs to care about it. A call to:

```
>>> device.ftdi_fn.ft_xyz(1, 2, 3)
```

is equivalent to the following:

```
>>> device.fdll.ft_xyz(ctypes.byref(device.ctx), 1, 2, 3)
```

but has the advantages of being shorter and not requiring `ctypes` to be in scope.

incorrect operations using any of these attributes of devices are liable to crash the Python interpreter

### Examples

The following example shows opening a device in serial mode, switching temporarily to bit-bang mode, then back to serial and writing a string. Why this would be wanted is anyone's guess ;-)

```
>>> from pylibftdi import Device
>>>
>>> with Device() as dev:
>>>     dev.ftdi_fn.ftdi_set_bitmode(1, 0x01)
>>>     dev.write('\x00\x01\x00')
>>>     dev.ftdi_fn.ftdi_set_bitmode(0, 0x00)
>>>     dev.write('Hello World!!!')
```

The `libftdi`<sup>9</sup> documentation should be consulted in conjunction with the `ctypes`<sup>10</sup> reference for guidance on using these features.

## 1.8 pylibftdi questions

None of these are yet frequently asked, and perhaps they never will be... But they are still questions, and they relate to `pylibftdi`.

---

<sup>9</sup> <http://www.intra2net.com/en/developer/libftdi/documentation/>

<sup>10</sup> <http://docs.python.org/library/ctypes.html>



## 1.8.1 Using pylibftdi - General

### Can I use pylibftdi with device XYZ?

If the device XYZ is (or uses as it's ) an FTDI device, then possibly. A large number of devices *will* work, but won't be recognised due to the limited USB Vendor and Product IDs which pylibftdi checks for.

To see the vendor / product IDs which are supported, run the following:

```
>>> from pylibftdi import USB_VID_LIST, USB_PID_LIST
>>> print (map (hex, USB_VID_LIST))
['0x403']
>>> print (map (hex, USB_PID_LIST))
['0x6001', '0x6010', '0x6011', '0x6014']
```

If a FTDI device with a VID / PID not matching the above is required, then the device's values should be appended to the appropriate list after import:

```
>>> from pylibftdi import USB_PID_LIST, USB_VID_LIST, Device
>>> USB_PID_LIST.append(0x1234)
>>>
>>> dev = Device() # will now recognise a device with PID 0x1234.
```

### Which devices are recommended?

While I used to do a lot of soldering, I prefer the cleaner way of breadboarding nowadays. As such I can strongly recommend the FTDI DIP modules which plug into a breadboard nice and easy, can be self-powered from USB, and can be re-used for dozens of different projects.

I've used (and test against) the following, all of which have 0.1" pin spacing in two rows 0.5" or 0.6" apart, so will sit across the central divide of any breadboard:

**UB232R** a small 8 pin device with mini-USB port; serial and CBUS bit-bang.

**UM245R** a 24-pin device with parallel FIFO modes. Full-size USB type B socket.

**UM232R** a 24-pin device with serial and bit-bang modes. Full-size USB type B socket.

**UM232H** this contains a more modern FT232H device, and libftdi support is fairly recent (requires 0.20 or later). Supports USB 2.0 Hi-Speed mode though, and lots of interesting modes (I2C, SPI, JTAG...) which I've not looked at yet. Mini-USB socket.

Personally I'd go with the UM232R device for compatibility. It works great with both UART and bit-bang IO, which I target as the two main use-cases for pylibftdi. The UM232H is certainly feature-packed though, and I hope to support some of the more interesting modes in future.

## 1.8.2 Using pylibftdi - Programming

### How do I set the baudrate?

In both serial and parallel mode, the internal baudrate generator (BRG) is set using the `baudrate` property of the `Device` instance. Reading this will show the current baudrate (which defaults to 9600); writing to it will attempt to set the BRG to that value.

On failure to set the baudrate, it will remain at its previous setting.

In parallel mode, the actual bytes-per-second rate of parallel data is 16x the programmed BRG value. This is an effect of the FTDI devices themselves, and is not hidden by pylibftdi.

### How do I send unicode over a serial connection?

If a `Device` instance is created with `mode='t'`, then text-mode is activated. This is analogous to opening files; after all, the API is intentionally modelled on file objects wherever possible.

When text-mode is used, an encoding can be specified. The default is `latin-1` for the very practical reason that it is transparent to 8-bit binary data; by default a text-mode serial connection looks just like a binary mode one.

An alternative encoding can be used provided in the same constructor call used to instantiate the `Device` class, e.g.:

```
>>> dev = Device(mode='t', encoding='utf-8')
```

Read and write operations will then return / take unicode values.

Whether it is sensible to try and send unicode over a ftdi connection is a separate issue... At least consider doing codec operations at a higher level in your application.

### How do I use multiple-interface devices?

Some FTDI devices have multiple interfaces, for example the FT2232H has 2 and the FT4232H has four. In terms of accessing them, they can be considered as independent devices; once a connection is established to one of them, it is isolated from the other interfaces.

To select which interface to use when opening a connection to a specific interface on a multiple-interface device, use the `interface_select` parameter of the `Device` (or `BitBangDevice`) class constructor. The value should be one of the following values. Symbolic constants are provided in the `pylibftdi` namespace.

<code>interface_select</code>	Meaning
<code>INTERFACE_ANY (0)</code>	Any interface
<code>INTERFACE_A (1)</code>	INTERFACE A
<code>INTERFACE_B (2)</code>	INTERFACE B
<code>INTERFACE_C (3)</code>	INTERFACE C
<code>INTERFACE_D (4)</code>	INTERFACE D

You should be able to open multiple `Devices` with different `interface_select` settings. *Thanks to Daniel Forer for testing multiple device support.*

### What is the difference between the `port` and `latch` `BitBangDevice` properties?

`latch` reflects the current state of the output latch (i.e. the last value written to the port), while `port` reflects input states as well. Writing to either `port` or `latch` has an identical effect, so when `pylibftdi` is used only for output, there is no effective difference, and `port` is recommended for simplicity and consistency.

The place where it does make a difference is during read-modify-write operations. Consider the following:

```
>>> dev = BitBangDevice() # 1
>>> dev.direction = 0x81 # 2 # set bits 0 and 7 are output
>>> dev.port = 0 # 3
>>> for _ in range(255): # 4
>>>     dev.port += 1 # 5 # read-modify-write operation
```

In this (admittedly contrived!) scenario, if one of the input lines D1..D6 were held low, then they would cause the counter to effectively ‘stop’. The += 1 operation would never actually set the bit as required (because it is an input at 0), and the highest output bit would never get set.

Using `dev.latch` in lines 3 and 5 above would resolve this, as the read-modify-write operation on line 5 is simply working on the in-memory latch value, rather than reading the inputs, and it would simply count up from 0 to 255 in steps of one, writing the value to the device (which would be ignored in the case of input lines).

Similar concepts exist in many microcontrollers, for example see <http://stackoverflow.com/a/2623498> for a possibly better explanation, though in a slightly different context :)

If you aren’t using read-modify-write operations (e.g. augmented assignment), or you have a direction on the port of either `ALL_INPUTS` (0) or `ALL_OUTPUTS` (1), then just ignore this section and use `port` :)

### What is the purpose of the `chunk_size` parameter?

While `libftdi` is performing I/O to the device, it is not really running Python code at all, but C library code via `ctypes`. If there is a significant amount of data, especially at low baud-rates, this can be a significant delay during which no Python bytecode is executed. The most obvious result of this is that no signals are delivered to the Python process during this time, and interrupt signals (Ctrl-C) will be ignored.

Try the following:

```
>>> dev = Device()
>>> dev.baudrate = 120 # nice and slow!
>>> dev.write('helloworld' * 1000)
```

This should take approximately 10 seconds prior to returning, and crucially, Ctrl-C interruptions will be deferred for all that time. By setting `chunk_size` on the device (which may be set either as a keyword parameter during `Device` instantiation, or at a later point as an attribute of the `Device` instance), the I/O operations are performed in chunks of at most the specified number of bytes. Setting it to 0, the default value, disables this chunking.

Repeat the above command but prior to the write operation, set `dev.chunk_size = 10`. A Ctrl-C interruption should now kick-in almost instantly. There is a performance trade-off however; if using `chunk_size` is required, set it as high as is reasonable for your application.

## 1.8.3 Using `pylibftdi` - Interfacing

### How do I control an LED?

`pylibftdi` devices generally have sufficient output current to sink or source the 10mA or so which a low(ish) current LED will need. A series resistor is essential to protect both the LED and the FTDI

device itself; a value between 220 and 470 ohms should be sufficient depending on required brightness / LED efficiency.

### How do I control a higher current device?

FTDI devices will typically provide a few tens of milli-amps, but beyond that things either just won't work, or the device could be damaged. For medium current operation, a standard bipolar transistor switch will suffice; for larger loads a MOSFET or relay should be used. (Note a relay will require a low-power transistor switch anyway). Search online for something like 'mosfet logic switch' or 'transistor relay switch' for more details.

### What is the state of an unconnected input pin?

This depends on the device and the EEPROM configuration values. Most devices will have weak (typ. 200Kohm) pull-ups on input pins, so there is no harm leaving them floating. Consult the datasheet for your device for definitive information, but you can always just leave an (unconnected) device and read it's pins when set as inputs; chances are they will read 255 / 0xFF:

```
>>> dev = BitBangDevice(direction=0)
>>> dev.port
255
```

While not recommended for anything serious, this does allow the possibility of reading a input switch state by simply connecting a switch between an input pin and ground (possibly with a low value - e.g. 100 ohm - series resistor to prevent accidents should it be set to an output and set high. . .). Note that with a normal push-to-make switch, the value will read '1' when the switch is not pressed; pressing it will set the input line value to '0'.

## 1.8.4 Developing pylibftdi

### How do I checkout and use the latest development version?

pylibftdi is currently developed with a Mercurial repository on bitbucket. To use / develop on that version, it must first be cloned locally, after which it can be 'installed'. Clone the repository to a local directory and install (with the 'develop' target ideally) as follows:

```
$ hg clone http://bitbucket.org/codedstructure/pylibftdi
$ cd pylibftdi
$ python setup.py develop
```

If permission-related issues occur, then consider using the `--user` flag to `setup.py` to install for only the local user, or try prefixing the above command with `sudo`.

Note for now there is only the master branch, so need to worry about which branch is required.

### How do I run the tests?

Tests aren't included in the distutils distribution, so clone the repository and run from there. pylibftdi supports Python 2.6/2.7 as well as Python 3.2+, so these tests can be run for each Python version:

```

$ hg clone http://bitbucket.org/codedstructure/pylibftdi
<various output stuff>
$ cd pylibftdi
$ python2.7 -m unittest discover
.....
-----
Ran 17 tests in 0.011s

OK
$ python3.3 -m unittest discover
.....
-----
Ran 17 tests in 0.015s

OK
$

```

### How can I determine and select the underlying libftdi library?

Since pylibftdi 0.12, the Driver exposes a `libftdi_version` method, which returns a tuple whose first three entries correspond to major, minor, and micro versions of the libftdi driver being used.

With the recent (early 2013) release of libftdi1 - which can coexist with the earlier 0.x versions - it is now possible to select which library to load when instantiating the Driver:

```

Python 2.7.2 (default, Jun 20 2012, 16:23:33)
[GCC 4.2.1 Compatible Apple Clang 4.0 (tags/Apple/clang-418.0.60)] on_
↳darwin
Type "help", "copyright", "credits" or "license" for more information.
>>> from pylibftdi import Driver
>>> Driver().libftdi_version()
(1, 0, 0, '1.0', 'v1.0-6-gafb9082')
>>> Driver('ftdi').libftdi_version()
(0, 99, 0, '0.99', 'v0.17-305-g50d77f8')
>>> Driver('libftdi1').libftdi_version()
(1, 0, 0, '1.0', 'v1.0-6-gafb9082')
>>> Driver(('libftdi1', 'libftdi')).libftdi_version()
(1, 0, 0, '1.0', 'v1.0-6-gafb9082')
>>> Driver(('libftdi', 'libftdi1')).libftdi_version()
(0, 99, 0, '0.99', 'v0.17-305-g50d77f8')
>>> Driver(('libftdi', 'libftdi1')).libftdi_version()

```

pylibftdi now prefers libftdi1 over libftdi, if both are installed. Since different OSs require different parameters to be given to find a library, the default search list given to `ctypes.util.find_library` is as follows:

```
Driver._dll_list = ('ftdi1', 'libftdi1', 'ftdi', 'libftdi')
```

This covers Windows (which requires the 'lib' prefix), Linux (which requires its absence), and Mac OS X, which is happy with either.

## 1.9 pylibftdi troubleshooting

Once up-and-running, pylibftdi is designed to be very simple, but sometimes getting it working in the first place can be more difficult.

### 1.9.1 Error messages

```
FtdiError: unable to claim usb device. Make sure the default FTDI driver is not in use (-5)
```

This indicates a conflict with FTDI's own drivers, and is (as far as I know) mainly a problem on Mac OS X, where they can be disabled (until reboot) by unloading the appropriate kernel module.

TODO: investigate ways of unloading the driver in the background e.g. as a part of some pylibftdi application startup itself?. The need to do this action as root may make things trickier.

#### OS X Mavericks, Yosemite and later

Starting with OS X Mavericks, OS X includes kernel drivers which will reserve the FTDI device by default. This needs unloading before *libftdi* will be able to communicate with the device:

```
sudo kextunload -bundle-id com.apple.driver.AppleUSBFTDI
```

Similarly to reload it:

```
sudo kextload -bundle-id com.apple.driver.AppleUSBFTDI
```

#### OS X Mountain Lion and earlier

Whereas Mavericks includes an FTDI driver directly, earlier versions of OS X did not, and if this issue occurred it would typically as a result of installing some other program - for example the Arduino IDE.

As a result, the kernel module may have different names, but *FTDIUSBSerialDriver.kext* is the usual culprit. Unload the kernel driver as follows:

```
sudo kextunload /System/Library/Extensions/FTDIUSBSerialDriver.kext
```

To reload the kernel driver, do the following:

```
sudo kextload /System/Library/Extensions/FTDIUSBSerialDriver.kext
```

If you aren't using whatever program might have installed it, the driver could be permanently removed (to prevent the need to continually unload it), but this is dangerous:

```
sudo rm /System/Library/Extensions/FTDIUSBSerialDriver.kext
```

Scripts are installed to perform these actions which are installed with pylibftdi; run *ftdi\_osx\_driver\_unload* to unload the kernel driver and *ftdi\_osx\_driver\_reload* to reload it. These commands are useful when other programs require frequent access to FTDI devices; the Arduino IDE running with FTDI devices (note many newer Arduino models use native USB rather than FTDI interfaces).

## 1.9.2 Diagnosis

Getting a list of USB devices

### Mac OS X

Start ‘System Information’, then select Hardware > USB, and look for your device. On the command line, `system_profiler SPUSBDataType` can be used. In the following example I’ve piped it into `grep -C 7 FTDI`, to print 7 lines either side of a match on the string ‘FTDI’:

```
ben$ system_profiler SPUSBDataType | grep -C 7 FTDI
    UM232H:

        Product ID: 0x6014
        Vendor ID: 0x0403 (Future Technology Devices International,
↳Limited)
        Version: 9.00
        Serial Number: FTUBIOWF
        Speed: Up to 480 Mb/sec
        Manufacturer: FTDI
        Location ID: 0x24710000 / 7
        Current Available (mA): 500
        Current Required (mA): 90

    USB Reader:

        Product ID: 0x4082
```

### Linux

Use `lsusb`. Example from my laptop:

```
ben@ben-laptop:~$ lsusb
Bus 001 Device 001: ID 1d6b:0002 Linux Foundation 2.0 root hub
Bus 002 Device 001: ID 1d6b:0002 Linux Foundation 2.0 root hub
Bus 003 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 004 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 005 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 006 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 007 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 008 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 008 Device 011: ID 0a5c:217f Broadcom Corp. Bluetooth Controller
Bus 002 Device 009: ID 17ef:481d Lenovo
Bus 002 Device 016: ID 0403:6014 Future Technology Devices International,
↳Ltd FT232H Single HS USB-UART/FIFO IC
```

## 1.9.3 Gathering information

Starting with `pylibftdi` version 0.15, an example script to gather system information is included, which will help in any diagnosis required.

Run the following:

```
python -m pylibftdi.examples.info
```

this will output a range of information related to the versions of libftdi libusb in use, as well as the system platform and Python version.

## 1.10 pylibftdi Package

### 1.10.1 pylibftdi Package

pylibftdi - python wrapper for libftdi

Copyright (c) 2010-2015 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

libftdi can be found at: <http://www.intra2net.com/en/developer/libftdi/>

Neither libftdi nor Intra2net are associated with this project; if something goes wrong here, it's almost definitely my fault rather than a problem with the libftdi library.

### 1.10.2 `_base` Module

pylibftdi - python wrapper for libftdi

Copyright (c) 2010-2015 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

**exception** `pylibftdi._base.FtdiError`

Bases: `exceptions.Exception`

**exception** `pylibftdi._base.LibraryMissingError`

Bases: `pylibftdi._base.FtdiError` (page 20)

### 1.10.3 `device` Module

pylibftdi.device - access to individual FTDI devices

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

**class** `pylibftdi.device.Device` (*device\_id=None, mode='b', encoding='latin1', lazy\_open=False, chunk\_size=0, interface\_select=None, device\_index=0, \*\*kwargs*)

Bases: `object`

Represents a connection to a single FTDI device

**\_\_init\_\_** (*device\_id=None, mode='b', encoding='latin1', lazy\_open=False, chunk\_size=0, interface\_select=None, device\_index=0, \*\*kwargs*)  
Device([device\_id[, mode, [OPTIONS ...]]) -> Device instance



represents a single FTDI device accessible via the libftdi driver. Supports a basic file-like interface (open/close/read/write, context manager support).

### Parameters

- **device\_id** – an optional serial number of the device to open. if omitted, this refers to the first device found, which is convenient if only one device is attached, but otherwise fairly useless.
- **mode** – either ‘b’ (binary) or ‘t’ (text). This primarily affects Python 3 calls to read() and write(), which will accept/return unicode strings which will be encoded/decoded according to the given. . .
- **encoding** – the codec name to be used for text operations.
- **lazy\_open** – if True, then the device will not be opened immediately - the user must perform an explicit open() call prior to other operations.
- **chunk\_size** – if non-zero, split read and write operations into chunks of this size. With large or slow accesses, interruptions (i.e. KeyboardInterrupt) may not happen in a timely fashion.
- **interface\_select** – select interface to use on multi-interface devices
- **device\_index** – optional index of the device to open, in the event of multiple matches for other parameters (PID, VID, device\_id). Defaults to zero (the first device found).

### close ()

close our connection, free resources

### flush (flush\_what=1)

Instruct the FTDI device to flush its FIFO buffers

By default both the input and output buffers will be flushed, but the caller can selectively chose to only flush the input or output buffers using *flush\_what*:

**Parameters flush\_what** – select what to flush: *FLUSH\_BOTH* (default); *FLUSH\_INPUT* (just the rx buffer); *FLUSH\_OUTPUT* (just the tx buffer)

### flush\_input ()

flush the device input buffer

### flush\_output ()

flush the device output buffer

### get\_error\_string ()

**Returns** error string from libftdi driver

### next ()

### open ()

open connection to a FTDI device

**read (length)** → bytes/string of up to ‘length’ bytes.

read upto *length* bytes from the FTDI device :param length: maximum number of bytes to read :return: value read from device :rtype: bytes if self.mode is ‘b’, else decode with self.encoding

**readline** (*size=0*)

readline() for file-like compatibility.

**Parameters** **size** – maximum amount of data to read looking for a line

**Returns** a line of text, or size bytes if no line-ending found

This only works for mode='t' on Python3

**readlines** (*sizehint=None*)

readlines() for file-like compatibility.

**write** (*data*) → count of bytes actually written

write given *data* string to the FTDI device

**Parameters** **data** (*string or bytes*) – string to be written

**Returns** count of bytes written, which may be less than *len(data)*

**writelines** (*lines*)

writelines for file-like compatibility.

**Parameters** **lines** – sequence of lines to write

**baudrate**

get or set the baudrate of the FTDI device. Re-read after setting to ensure baudrate was accepted by the driver.

**closed**

The Python file API defines a read-only 'closed' attribute

**ftdi\_fn**

this allows the vast majority of libftdi functions which are called with a pointer to a ftdi\_context struct as the first parameter to be called here preventing the need to leak self.ctx into the user code (and import byref from ctypes):

```
>>> with Device() as dev:
...     # set 8 bit data, 2 stop bits, no parity
...     dev.ftdi_fn.ftdi_set_line_property(8, 2, 0)
... 
```

## 1.10.4 driver Module

pylibftdi.driver - interface to the libftdi library

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

**class** pylibftdi.driver.**Driver** (*libftdi\_search=None*)

Bases: object

This is where it all happens... We load the libftdi library, and use it.

**\_\_init\_\_** (*libftdi\_search=None*)

**Parameters** **libftdi\_search** (*string or sequence of strings*) – force a particular version of libftdi to be used can specify either library name(s) or path(s)

**libftdi\_version()**

**Returns** the version of the underlying library being used

**Return type** tuple (major, minor, micro, version\_string, snapshot\_string)

**libusb\_version()**

**Returns** namedtuple containing version info on libusb

**list\_devices()**

**Returns**

(manufacturer, description, serial#) for each attached device, e.g.:

```
[('FTDI', 'UM232R USB <-> Serial', 'FTE4FFVQ'), ('FTDI', 'UM245R',
'FTE00P4L')]
```

**Return type** a list of string triples

the serial number can be used to open specific devices

**fdll**

ctypes DLL referencing the libftdi library

This is the main interface to FTDI functionality.

```
class pylibftdi.driver.ftdi_device_list
```

Bases: `_ctypes.Structure`

**dev**

Structure/Union member

**next**

Structure/Union member

```
class pylibftdi.driver.ftdi_version_info
```

Bases: `_ctypes.Structure`

**major**

Structure/Union member

**micro**

Structure/Union member

**minor**

Structure/Union member

**snapshot\_str**

Structure/Union member

**version\_str**

Structure/Union member

```
class pylibftdi.driver.libftdi_version(major, minor, micro, version_str,
                                       snapshot_str)
```

Bases: `tuple`

**major**

Alias for field number 0

**micro**

Alias for field number 2

**minor**

Alias for field number 1

**snapshot\_str**

Alias for field number 4

**version\_str**

Alias for field number 3

**class** pylibftdi.driver.libusb\_version(*major, minor, micro, nano, rc, describe*)

Bases: tuple

**describe**

Alias for field number 5

**major**

Alias for field number 0

**micro**

Alias for field number 2

**minor**

Alias for field number 1

**nano**

Alias for field number 3

**rc**

Alias for field number 4

**class** pylibftdi.driver.libusb\_version\_struct

Bases: ctypes.Structure

**describe**

Structure/Union member

**major**

Structure/Union member

**micro**

Structure/Union member

**minor**

Structure/Union member

**nano**

Structure/Union member

**rc**

Structure/Union member

### 1.10.5 bitbang Module

pylibftdi - python wrapper for libftdi

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

```
class pylibftdi.bitbang.BitBangDevice (device_id=None, direction=255,
                                       lazy_open=False, sync=True, bit-
                                       bang_mode=1, interface_select=None,
                                       **kwargs)
```

Bases: `pylibftdi.device.Device` (page 20)

simple subclass to support bit-bang mode

Internally uses async mode at the moment, but provides a 'sync' flag (defaulting to True) which controls the behaviour of port reading and writing - if set, the FIFOs are ignored (read) or cleared (write) so operations will appear synchronous

**Adds two read/write properties to the base class:** direction: 8 bit input(0)/output(1) direction control. port: 8 bit IO port, as defined by direction.

```
__init__ (device_id=None, direction=255, lazy_open=False, sync=True, bit-
          bang_mode=1, interface_select=None, **kwargs)
Device([device_id[, mode, [OPTIONS ... ]]) -> Device instance
```

represents a single FTDI device accessible via the libftdi driver. Supports a basic file-like interface (open/close/read/write, context manager support).

#### Parameters

- **device\_id** – an optional serial number of the device to open. if omitted, this refers to the first device found, which is convenient if only one device is attached, but otherwise fairly useless.
- **mode** – either 'b' (binary) or 't' (text). This primarily affects Python 3 calls to read() and write(), which will accept/return unicode strings which will be encoded/decoded according to the given...
- **encoding** – the codec name to be used for text operations.
- **lazy\_open** – if True, then the device will not be opened immediately - the user must perform an explicit open() call prior to other operations.
- **chunk\_size** – if non-zero, split read and write operations into chunks of this size. With large or slow accesses, interruptions (i.e. KeyboardInterrupt) may not happen in a timely fashion.
- **interface\_select** – select interface to use on multi-interface devices
- **device\_index** – optional index of the device to open, in the event of multiple matches for other parameters (PID, VID, device\_id). Defaults to zero (the first device found).

```
open ()
    open connection to a FTDI device
```

```
read_pins ()
    read the current 'actual' state of the pins
```

**Returns** 8-bit binary representation of pin state

**Return type** int

**direction**

get or set the direction of each of the IO lines. LSB=D0, MSB=D7 1 for output, 0 for input

**latch**

latch property - the output latch (in-memory representation of output pin state)

Note `_latch` is not masked by direction (except on initialisation), as otherwise a loop incrementing a mixed input/output port would not work, as it would 'stop' on input pins. This is the primary use case for 'latch'. It's basically a *port* which ignores input.

**Returns** the state of the output latch

**port**

get or set the state of the IO lines. The value of output lines is persisted in this object for the purposes of reading, so read-modify-write operations (e.g. `drv.port+=1`) are valid.

### 1.10.6 serial\_device Module

pylibftdi - python wrapper for libftdi

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

```
class pylibftdi.serial_device.SerialDevice (device_id=None, mode='b',
                                             encoding='latin1',
                                             lazy_open=False,
                                             chunk_size=0, interface_select=None, device_index=0, **kwargs)
```

Bases: `pylibftdi.device.Device` (page 20)

simple subclass to support serial(rs232) lines

cts, dsr, ri - input dtr, rts - output

Note: These lines are all active-low by default, though this can be changed in the EEPROM settings. pylibftdi does not attempt to hide these settings, and simply writes out the given values (i.e. '1' will typically make an output line 'active' - and therefore low)

**cts**

get the state of CTS (1 = 'active')

**dsr**

get the state of DSR (1 = 'active')

**dtr**

set (or get the previous set) state of the DTR line

**Returns** the state of the DTR line; None if not previously set

**ri**

get the state of RI (1 = 'active')

**rts**

set (or get the previous set) state of the DTR line

**Returns** the state of the RTS line; None if not previously set

## 1.10.7 util Module

pylibftdi - python wrapper for libftdi

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> See LICENSE file for details and (absence of) warranty

pylibftdi: <http://bitbucket.org/codedstructure/pylibftdi>

**class** pylibftdi.util.**Bus** (*offset, width=1*)

Bases: object

This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a BitBangDevice instance in the 'device' attribute of the object to which this is attached.

**\_\_init\_\_** (*offset, width=1*)

x.**\_\_init\_\_**(...) initializes x; see help(type(x)) for signature

## 1.10.8 Subpackages

### examples Package

#### examples Package

pylibftdi examples

### bit\_server Module

bit\_server.py - remote HTTP interface to bit-banged FTDI port This runs as a web server, connect to port 8008

Change HTTP\_PORT for different port number or supply alternate as args[1]

#### Requires:

- pylibftdi

**class** pylibftdi.examples.bit\_server.**ReqHandler** (*request, client\_address, server*)

Bases: BaseHTTPServer.BaseHTTPRequestHandler

**do\_GET** ()

**do\_POST** ()

**send\_head** ()

**class** pylibftdi.examples.bit\_server.**ThreadingServer** (*server\_address, RequestHandler-Class, bind\_and\_activate=True*)  
Bases: SocketServer.ThreadingMixIn, BaseHTTPServer.HTTPServer

pylibftdi.examples.bit\_server.**get\_page** ()

pylibftdi.examples.bit\_server.**runserver** (*port=8008*)

## lcd Module

Write a string (argv[1] if run from command line) to a HD44780 LCD module connected via a FTDI UM232R/245R module using pylibftdi

example usage:

```
# while true; > do python lcd.py $( awk '{print $1}' /proc/loadavg); > sleep 5; > done
```

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> All rights reserved.

```
class pylibftdi.examples.lcd.LCD (device)
```

```
    Bases: object
```

**The UM232R/245R is wired to the LCD as follows:** DB0..3 to LCD D4..D7 (pin 11..pin 14)  
DB6 to LCD 'RS' (pin 4) DB7 to LCD 'E' (pin 6)

```
__init__ (device)
```

```
    x.__init__(...) initializes x; see help(type(x)) for signature
```

```
init_four_bit ()
```

```
    set the LCD's 4 bit mode, since we only have 8 data lines and need at least 2 to strobe data into the module and select between data and commands.
```

```
write_cmd (x)
```

```
write_data (x)
```

```
data
```

```
    This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a BitBangDevice instance in the 'device' attribute of the object to which this is attached.
```

```
e
```

```
    This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a BitBangDevice instance in the 'device' attribute of the object to which this is attached.
```

```
rs
```

```
    This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a BitBangDevice instance in the 'device' attribute of the object to which this is attached.
```

```
pylibftdi.examples.lcd.display (string, device_id=None)
```

```
    Display the given string on an attached LCD an optional device_id can be given.
```

## led\_flash Module

Flash an LED connected via a FTDI UM232R/245R module using pylibftdi

Optionally supply a flash rate (in Hz, default 1) as an argument

Copyright (c) 2010-2014 Ben Bass <benbass@codedstructure.net> All rights reserved.

```
pylibftdi.examples.led_flash.flash_forever (rate)
```

```
    toggle bit zero at rate Hz
```

```
pylibftdi.examples.led_flash.main ()
```



## list\_devices Module

Report connected FTDI devices. This may be useful in obtaining serial numbers to use as the `device_id` parameter of the `Device()` constructor to communicate with a specific device when more than one is present.

example usage:

```
$ python pylibftdi/examples/list_devices.py FTDI:UB232R:FTAS1UN5 FTDI:UM232R
USB <-> Serial:FTE4FFVQ
```

To open a device specifically to communicate with the second of these devices, the following would be used:

```
>>> from pylibftdi import Device
>>> dev = Device(device_id="FTE4FFVQ")
>>>
```

Copyright (c) 2011-2014 Ben Bass <[benbass@codedstructure.net](mailto:benbass@codedstructure.net)> All rights reserved.

```
pylibftdi.examples.list_devices.get_ftdi_device_list()
    return a list of lines, each a colon-separated vendor:product:serial summary of detected devices
```

## magic\_candle Module

**Magic Candle - light falling on the LDR turns on the LED, which due** to arrangement keeps the LED on until LDR/LED path is blocked

LDR (via a transistor switch - dark = '1') - D0 LED (via series resistor) - D1

pylibftdi - codedstructure 2013-2014

```
class pylibftdi.examples.magic_candle.Candle
```

```
    Bases: object
```

```
    __init__()
```

```
        x.__init__(...) initializes x; see help(type(x)) for signature
```

```
    run()
```

```
    be_light
```

This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a `BitBangDevice` instance in the 'device' attribute of the object to which this is attached.

```
    is_dark
```

This class is a descriptor for a bus of a given width starting at a given offset (0 = LSB). The device which does the actual reading and writing is assumed to be a `BitBangDevice` instance in the 'device' attribute of the object to which this is attached.

## midi\_output Module

```
class pylibftdi.examples.midi_output.MidiDevice(*o, **k)
```

```
    Bases: pylibftdi.device.Device (page 20)
```

`__init__`(\*o, \*\*k)

Device([device\_id[, mode, [OPTIONS ...]]) -> Device instance

represents a single FTDI device accessible via the libftdi driver. Supports a basic file-like interface (open/close/read/write, context manager support).

#### Parameters

- **device\_id** – an optional serial number of the device to open. if omitted, this refers to the first device found, which is convenient if only one device is attached, but otherwise fairly useless.
- **mode** – either ‘b’ (binary) or ‘t’ (text). This primarily affects Python 3 calls to read() and write(), which will accept/return unicode strings which will be encoded/decoded according to the given...
- **encoding** – the codec name to be used for text operations.
- **lazy\_open** – if True, then the device will not be opened immediately - the user must perform an explicit open() call prior to other operations.
- **chunk\_size** – if non-zero, split read and write operations into chunks of this size. With large or slow accesses, interruptions (i.e. KeyboardInterrupt) may not happen in a timely fashion.
- **interface\_select** – select interface to use on multi-interface devices
- **device\_index** – optional index of the device to open, in the event of multiple matches for other parameters (PID, VID, device\_id). Defaults to zero (the first device found).

```
pylibftdi.examples.midi_output.scale()
```

```
pylibftdi.examples.midi_output.volume(beat)
```

#### pin\_read Module

Display values on input pins of a BitBangDevice.

#### TODO:

- ANSI colours / display differences in bold

**example - beep on pin 1 going high:** \$ pylibftdi/examples/pin\_read.py -n 0.01 -m 1 -k 1 && beep

Copyright (c) 2011-2014 Ben Bass <benbass@codedstructure.net> All rights reserved.

```
pylibftdi.examples.pin_read.display_loop(interval=1, count=0, match=None,  
                                         mask=255)
```

display and compare the value

#### Parameters

- **interval** – polling interval in seconds
- **count** – number of polls to do, or infinite if 0
- **match** – value to look for to exit early
- **mask** – mask of read value before comparing to match

**Returns** ‘ok’. either a match was made or none was requested

**Return type** bool

`pylibftdi.examples.pin_read.display_value (value)`  
display the given value

`pylibftdi.examples.pin_read.get_value ()`  
get the value of the pins

`pylibftdi.examples.pin_read.main (args=None)`

**serial\_loopback Module**

test serial loopback; assumes Rx and Tx are connected

Copyright (c) 2010-2014 Ben Bass <[benbass@codedstructure.net](mailto:benbass@codedstructure.net)> All rights reserved.

**class** `pylibftdi.examples.serial_loopback.LoopbackTester`

Bases: object

`__init__ ()`

x.`__init__ (...)` initializes x; see `help(type(x))` for signature

`main ()`

`test_loopback (lengths)`

`pylibftdi.examples.serial_loopback.test_string (length)`

**info Module**

Report environment info relevant to pylibftdi

example usage:

```
$ python3 -m pylibftdi.examples.info
pylibftdi version      : 0.15.0
libftdi version       : libftdi_version(major=1, minor=1, micro=0, version_
↳str=b'1.1', snapshot_str=b'unknown')
libftdi library path  : /usr/local/lib/libftdi1.dylib
libusb version        : libusb_version(major=1, minor=0, micro=19,
↳nano=10903, rc=b'', describe=b'http://libusb.info')
libusb library path   : /usr/local/lib/libusb-1.0.dylib
Python version        : 3.4.0
OS platform           : Darwin-14.1.0-x86_64-i386-64bit
```

Copyright (c) 2015 Ben Bass <[benbass@codedstructure.net](mailto:benbass@codedstructure.net)>

`pylibftdi.examples.info.ftdi_info ()`

Return (ordered) dictionary containing pylibftdi environment info

Designed for display purposes only; keys and value types may vary.



## CHAPTER 2

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



### p

- `pylibftdi.__init__`, 20
- `pylibftdi._base`, 20
- `pylibftdi.bitbang`, 24
- `pylibftdi.device`, 20
- `pylibftdi.driver`, 22
- `pylibftdi.examples`, 27
  - `pylibftdi.examples.bit_server`, 27
  - `pylibftdi.examples.info`, 31
  - `pylibftdi.examples.lcd`, 28
  - `pylibftdi.examples.led_flash`, 28
  - `pylibftdi.examples.list_devices`, 29
  - `pylibftdi.examples.magic_candle`, 29
  - `pylibftdi.examples.midi_output`, 29
  - `pylibftdi.examples.pin_read`, 30
  - `pylibftdi.examples.serial_loopback`, 31
- `pylibftdi.serial_device`, 26
- `pylibftdi.util`, 27





## Symbols

- \_\_init\_\_()** (*pylibftdi.bitbang.BitBangDevice* method), 25  
**\_\_init\_\_()** (*pylibftdi.device.Device* method), 20  
**\_\_init\_\_()** (*pylibftdi.driver.Driver* method), 22  
**\_\_init\_\_()** (*pylibftdi.examples.lcd.LCD* method), 28  
**\_\_init\_\_()** (*pylibftdi.examples.magic\_candle.Candle* method), 29  
**\_\_init\_\_()** (*pylibftdi.examples.midi\_output.MidiDevice* method), 29  
**\_\_init\_\_()** (*pylibftdi.examples.serial\_loopback.LoopbackTester* method), 31  
**\_\_init\_\_()** (*pylibftdi.util.Bus* method), 27
- B**  
 baudrate (*pylibftdi.device.Device* attribute), 22  
 be\_light (*pylibftdi.examples.magic\_candle.Candle* attribute), 29  
 BitBangDevice (class in *pylibftdi.bitbang*), 25  
 Bus (class in *pylibftdi.util*), 27
- C**  
 Candle (class in *pylibftdi.examples.magic\_candle*), 29  
 close() (*pylibftdi.device.Device* method), 21  
 closed (*pylibftdi.device.Device* attribute), 22  
 cts (*pylibftdi.serial\_device.SerialDevice* attribute), 26
- D**  
 data (*pylibftdi.examples.lcd.LCD* attribute), 28  
 describe (*pylibftdi.driver.libusb\_version* attribute), 24  
 describe (*pylibftdi.driver.libusb\_version\_struct* attribute), 24  
 dev (*pylibftdi.driver.ftdi\_device\_list* attribute), 23  
 Device (class in *pylibftdi.device*), 20  
 direction (*pylibftdi.bitbang.BitBangDevice* attribute), 25  
 display() (in module *pylibftdi.examples.lcd*), 28  
 display\_loop() (in module *pylibftdi.examples.pin\_read*), 30  
 display\_value() (in module *pylibftdi.examples.pin\_read*), 31  
 do\_GET() (*pylibftdi.examples.bit\_server.ReqHandler* method), 27  
 do\_POST() (*pylibftdi.examples.bit\_server.ReqHandler* method), 27  
 Driver (class in *pylibftdi.driver*), 22  
 dsr (*pylibftdi.serial\_device.SerialDevice* attribute), 26  
 dtr (*pylibftdi.serial\_device.SerialDevice* attribute), 26
- E**  
 e (*pylibftdi.examples.lcd.LCD* attribute), 28
- F**  
 fdll (*pylibftdi.driver.Driver* attribute), 23  
 flash\_forever() (in module *pylibftdi.examples.led\_flash*), 28  
 flush() (*pylibftdi.device.Device* method), 21  
 flush\_input() (*pylibftdi.device.Device* method), 21  
 flush\_output() (*pylibftdi.device.Device* method), 21  
 ftdi\_device\_list (class in *pylibftdi.driver*), 23  
 ftdi\_fn (*pylibftdi.device.Device* attribute), 22  
 ftdi\_info() (in module *pylibftdi.examples.info*), 31  
 ftdi\_version\_info (class in *pylibftdi.driver*), 23

FtdiError, 20

## G

get\_error\_string() (pylibftdi.device.Device method), 21  
 get\_ftdi\_device\_list() (in module pylibftdi.examples.list\_devices), 29  
 get\_page() (in module pylibftdi.examples.bit\_server), 27  
 get\_value() (in module pylibftdi.examples.pin\_read), 31

## I

init\_four\_bit() (pylibftdi.examples.lcd.LCD method), 28  
 is\_dark (pylibftdi.examples.magic\_candle.Candle attribute), 29

## L

latch (pylibftdi.bitbang.BitBangDevice attribute), 26  
 LCD (class in pylibftdi.examples.lcd), 28  
 libftdi\_version (class in pylibftdi.driver), 23  
 libftdi\_version() (pylibftdi.driver.Driver method), 22  
 LibraryMissingError, 20  
 libusb\_version (class in pylibftdi.driver), 24  
 libusb\_version() (pylibftdi.driver.Driver method), 23  
 libusb\_version\_struct (class in pylibftdi.driver), 24  
 list\_devices() (pylibftdi.driver.Driver method), 23  
 LoopbackTester (class in pylibftdi.examples.serial\_loopback), 31

## M

main() (in module pylibftdi.examples.led\_flash), 28  
 main() (in module pylibftdi.examples.pin\_read), 31  
 main() (pylibftdi.examples.serial\_loopback.LoopbackTester method), 31  
 major (pylibftdi.driver.ftdi\_version\_info attribute), 23  
 major (pylibftdi.driver.libftdi\_version attribute), 23  
 major (pylibftdi.driver.libusb\_version attribute), 24

major (pylibftdi.driver.libusb\_version\_struct attribute), 24  
 micro (pylibftdi.driver.ftdi\_version\_info attribute), 23  
 micro (pylibftdi.driver.libftdi\_version attribute), 23  
 micro (pylibftdi.driver.libusb\_version attribute), 24  
 micro (pylibftdi.driver.libusb\_version\_struct attribute), 24  
 MidiDevice (class in pylibftdi.examples.midi\_output), 29  
 minor (pylibftdi.driver.ftdi\_version\_info attribute), 23  
 minor (pylibftdi.driver.libftdi\_version attribute), 24  
 minor (pylibftdi.driver.libusb\_version attribute), 24  
 minor (pylibftdi.driver.libusb\_version\_struct attribute), 24

## N

nano (pylibftdi.driver.libusb\_version attribute), 24  
 nano (pylibftdi.driver.libusb\_version\_struct attribute), 24  
 next (pylibftdi.driver.ftdi\_device\_list attribute), 23  
 next() (pylibftdi.device.Device method), 21

## O

open() (pylibftdi.bitbang.BitBangDevice method), 25  
 open() (pylibftdi.device.Device method), 21

## P

port (pylibftdi.bitbang.BitBangDevice attribute), 26  
 pylibftdi.\_\_init\_\_ (module), 20  
 pylibftdi.\_base (module), 20  
 pylibftdi.bitbang (module), 24  
 pylibftdi.device (module), 20  
 pylibftdi.driver (module), 22  
 pylibftdi.examples (module), 27  
 pylibftdi.examples.bit\_server (module), 27  
 pylibftdi.examples.info (module), 31  
 pylibftdi.examples.lcd (module), 28  
 pylibftdi.examples.led\_flash (module), 28  
 pylibftdi.examples.list\_devices (module), 29

pylibftdi.examples.magic\_candle (module), 29  
 pylibftdi.examples.midi\_output (module), 29  
 pylibftdi.examples.pin\_read (module), 30  
 pylibftdi.examples.serial\_loopback (module), 31  
 pylibftdi.serial\_device (module), 26  
 pylibftdi.util (module), 27

## R

rc (pylibftdi.driver.libusb\_version attribute), 24  
 rc (pylibftdi.driver.libusb\_version\_struct attribute), 24  
 read() (pylibftdi.device.Device method), 21  
 read\_pins() (pylibftdi.bitbang.BitBangDevice method), 25  
 readline() (pylibftdi.device.Device method), 21  
 readlines() (pylibftdi.device.Device method), 22  
 ReqHandler (class in pylibftdi.examples.bit\_server), 27  
 ri (pylibftdi.serial\_device.SerialDevice attribute), 26  
 rs (pylibftdi.examples.lcd.LCD attribute), 28  
 rts (pylibftdi.serial\_device.SerialDevice attribute), 26  
 run() (pylibftdi.examples.magic\_candle.Candle method), 29  
 runserver() (in module pylibftdi.examples.bit\_server), 27

## S

scale() (in module pylibftdi.examples.midi\_output), 30  
 send\_head() (pylibftdi.examples.bit\_server.ReqHandler method), 27  
 SerialDevice (class in pylibftdi.serial\_device), 26  
 snapshot\_str (pylibftdi.driver.ftdi\_version\_info attribute), 23  
 snapshot\_str (pylibftdi.driver.libftdi\_version attribute), 24

## T

test\_loopback() (pylibftdi.examples.serial\_loopback.LoopbackTester method), 31  
 test\_string() (in module pylibftdi.examples.serial\_loopback), 31  
 ThreadingServer (class in pylibftdi.examples.bit\_server), 27

## V

version\_str (pylibftdi.driver.ftdi\_version\_info attribute), 23  
 version\_str (pylibftdi.driver.libftdi\_version attribute), 24  
 volume() (in module pylibftdi.examples.midi\_output), 30

## W

write() (pylibftdi.device.Device method), 22  
 write\_cmd() (pylibftdi.examples.lcd.LCD method), 28  
 write\_data() (pylibftdi.examples.lcd.LCD method), 28  
 writelines() (pylibftdi.device.Device method), 22